NEW YORK UNIVERSITY

Institute of Mathematical Sciences

Division of Electromagnetic Research

RESEARCH REPORT No. EM-107

The Inverse Laplace Transform of an Exponential Function

F. M. RAGAB

THE INVERSE LAPLACE TRANSFORM OF AN EXPONENTIAL FUNCTION

F. M. Ragab

F. M. Ragab
─────────────

Morris Kline
Project Director

July, 1957

Table of Contents

Abstract

The inverse Laplace transform of the image function $p^{a-1}\exp(-a^{\frac{1}{m}} p^{\frac{1}{m}})$, which arises in electromagnetic diffraction theory, is obtained and the asymptotic behavior of the original function for values of the independent variable near 0 is then determined.

1. Introduction

In electromagnetic problems one often has occasion to study pulse fields, that is, fields created by sources which have a Heaviside unit function behavior or a delta-function behavior in the time variable as well as fields created by the same sources and having a harmonic time behavior. The latter fields also prove to be harmonic in time (apart from a transient) and these time harmonic fields are the Laplace transforms of the corresponding pulse fields[7]. It is also true that if one expands the pulse solution of Maxwell's equations (or the scalar wave equation) in powers of $(t-t_o)$ where t_o is a singularity of the pulse solution and if one obtains an asymptotic series representation of the spatial behavior of the corresponding time harmonic field in powers of $1/\omega$ where ω is the circular frequency of the source, then the individual terms of the asymptotic series are essentially Laplace transforms of the corresponding terms in the series of powers of $t-t_o$ (see eq. (4.8) of [8]).

To extend the knowledge of the relationship between time harmonic fields and pulse fields and between the asymptotic series described above and the corresponding series of powers to fields diffracted by smooth bodies, it now appears desirable to utilize some Laplace transforms which have not been established. The present paper is concerned with determining the original function whose Laplace transform is

(1) $$p^{\alpha-1} \exp\left[-a^{1/m} p^{1/m}\right],$$

where p, as usual, is complex, $R(p) > 0$, $R(\alpha) > 0$, $R(a) > 0$ and $m = 2,3,4,\dots$. It is expected that the result will be useful in electromagnetic diffraction problems but the present paper will be devoted to the purely mathematical problem of determining the original function and also the asymptotic behavior of the original function for t near 0.

When $m = 2$ the function (1) is, of course,

(2) $$p^{\alpha-1} \exp\left[-a^{1/2} \, p^{1/2}\right]$$

and the original function is known (see [1], p. 246, eq. 9). It is in fact the
function

(3) $$2^{\frac{1}{2} - \alpha} \; \pi^{-\frac{1}{2}} \; t^{-\alpha} \; e^{-\frac{a}{8t}} \; D_{2\alpha-1}\left(2^{-\frac{1}{2}} \, a^{\frac{1}{2}} \, t^{-\frac{1}{2}}\right)$$

where $R(a) > 0$, $R(\alpha) > 0$ and $D_\nu(z)$ is the parabolic cylinder function (see [2], p. 392)

$$D_\nu(z) = 2^{\frac{\nu}{2} + \frac{1}{4}} \; z^{-\frac{1}{2}} \; W_{\frac{\nu}{2} + \frac{1}{4}, \pm \frac{1}{4}}\left(\frac{z^2}{2}\right)$$

(4)
$$= \frac{2^{-\nu-1} z^\nu}{\pi^{1/2} \Gamma(-\nu)} \; e^{-z^2/4} \; E\left(-\frac{\nu}{2}, \frac{1}{2} - \frac{\nu}{2} :: \frac{z^2}{2}\right) \; .$$

The function appearing on the right side of this last equation is MacRobert's
E-function whose definition and properties are to be found in the literature
(see [3], p. 348 and 352 or [6], pp. 203-206) and about which more will be said
below. Hence the major result of this paper is a generalization of the Laplace
transform relationship between the functions (3) and (2) to the case where the
exponents in the exponential part of (2) are 1/m. The result will be stated and
derived in Section 2. After deriving a subsidiary formula in Section 2 we show
in Section 4 that the general result of Section 2 reduces to the special case
when m = 2. In Section 5 we derive the asymptotic behavior as t approaches 0 of
the inverse Laplace transform of the function (1).

2. Derivation of the original function

We present first for convenient reference several facts about the E-function
and other relationships which will be utilized later. We begin with some facts
about the generalized hypergeometric function.

The symbols (k;0) and k;n), where k may be real or complex, are defined as

$$(k;0) = 1$$

$$(k;n) = k(k+1)(k+2)...(k+n-1), \qquad n = 1,2,3,... \quad .$$

Then the generalized hypergeometric function $F(p;a_r:q;\rho_s:z)$ is defined as

$$F(p;a_r:q;\rho_s:z) = \sum_{n=0}^{\infty} \frac{(a_1;n)(a_2;n)...(a_p;n)}{n!(\rho_1;n)(\rho_2;n)...(\rho_q;n)} \; z^n$$

wherein it is assumed that none of the ρ's is zero or a negative integer. An alternative notation for this F-function is

$$F \begin{pmatrix} a_1,a_2,....,a_p;z \\ \rho_1,\rho_2,...,\rho_q \end{pmatrix} \quad .$$

When $p = 1$ and $q = 1$, the generalized hypergeometric function $F(1;a:1;o:z)$ is often denoted as $F(a;\rho;z)$ or as $_1F_1(a;\rho;z)$.

If $p \leq q$ then the E-function is defined as

$$E(p;a_r:q;\rho_s:z) = \frac{\Gamma(a_1)\Gamma(a_2)...\Gamma(a_p)}{\Gamma(\rho_1)\Gamma(\rho_2)...\Gamma(\rho_q)} F(p;a_r:q;\rho_s: -\frac{1}{z})$$

where $z \neq 0$. If $p \geq q+1$, and this is the case which will be of interest here, and when $|amp \; z| < \pi$, then the E-function (see p. 353) can be shown to be [3] *

$$E(p;a_r:q;\rho_s:z) = \sum_{r=1}^{p} \prod_{s=1}^{p}{}' \Gamma(a_s-a_r) \left\{ \prod_{t=1}^{q} \Gamma(\rho_t-a_r) \right\}^{-1} \Gamma(a_r) \; \bullet$$

(5)

$$z^{a_r} F \begin{pmatrix} a_r,a_r-\rho_1+1,...a_r-\rho_q+1;(-1)^{p-q}z \\ a_r-a_1+1,... * ..., a_r-a_p+1 \end{pmatrix}$$

* The definition of the E-function for this case is given in the Appendix where it is utilized.

where the dash in the product sign signifies that the factor for which s = r is omitted and the asterisk in the F function means that the parameter $\alpha_r - \alpha_r + 1$ is omitted, so that there are only p-1 parameters in the lower set. When there are no ρ_s's in the E-function, that is, when q = 0, then equation (5) holds under the conditions that the factor in the braces is omitted and the parameters $\alpha_r - \rho_1 + 1$, ..., $\alpha_r - \rho_q + 1$ are omitted in the F-function.

To familiarize ourselves with the E-function the following relations may be worth noting though they will not be used. From the definition of the E-function for the case p ≤ q and from equation (5) it is clear that the E-function is immediately related to the generalized hypergeometric function and reduces to simple expressions in the ordinary or Gauss hypergeometric function when p = 2 and q = 1. For p = 1 and q = 1 it is also evident from the definition that the F-function reduces to the confluent hypergeometric function or Kummer's function. The case p = 2, q = 0 yields the following relation (see [3], p. 351, eq. (14))

$$\cos n\pi E(\tfrac{1}{2} + n, \tfrac{1}{2} - n :: 2z) = \sqrt{2\pi z} \; e^z \; K_n(z)$$

where $K_n(z)$ is the modified Bessel function of the second kind. It is also true that

$$E(\tfrac{1}{2} - k + m, \tfrac{1}{2} - k - m :: z) = \Gamma(\tfrac{1}{2} - k + m) \Gamma(\tfrac{1}{2} - k - m) z^{-k} e^{\tfrac{1}{2} z} W_{k,m}(z)$$

where $W_{k,m}(z)$ is the Whittaker function (see [3], p. 351, eq. (15)). Finally it is immediate from the definition of the E-function that for p = 0 and q = 0 the F-function is just $e^{-1/z}$. More complicated parameters in the E-function lead to the equivalence of the E-function with products of Hankel functions, with Lommel functions, and with products of Whittaker functions (see [3], p. 395).

We shall utilize the relationship

$$(6) \qquad \int_0^\infty e^{-\lambda} \lambda^{\alpha_{p+1} - 1} E(p; \alpha_r : q; \rho_s : z/\lambda) d\lambda = E(p+1; \alpha_r : q; \rho_s : z)$$

where $R(\alpha_{p+1}) > 0$. This equation will be proven in Appendix I.

Other equations we shall use are

$$(7) \qquad \Gamma(z)\Gamma(z+\tfrac{1}{m}) \dots \Gamma(z+\tfrac{m-1}{m}) = (2\pi)^{\tfrac{m}{2}-\tfrac{1}{2}} m^{\tfrac{1}{2}-mz} \Gamma(mz)$$

which is the multiplication equation of Gauss and Legendre (see [6], p. 4, eq. (11));

$$(8) \qquad \Gamma(z)\Gamma(1-z) = \frac{\pi}{\sin\pi z}$$

(see [6], p. 3, eq. (6)) ;

$$(9) \qquad {}_1F_1(\alpha;\rho;z) = e^z \, {}_1F_1(\rho-\alpha;\rho;-z)$$

(see [3], p. 346, eq. (5));and the common trigonometric identity

$$(10) \qquad \sin\frac{\pi}{m}\sin\frac{2\pi}{m} \dots \sin\frac{m-1}{m}\pi = 2^{1-m}m.$$

We shall be interested in the E-function when there are no ρ_s's, that is, when q = 0 and when the p parameters α_r are the m parameters α, $\alpha + \frac{1}{m}$, $\alpha + \frac{2}{m}$, ..., $\alpha + \frac{m-1}{m}$. Then we shall use the accepted notation

$$E(\alpha,\alpha+\frac{1}{m},\ \alpha+\frac{2}{m},\ \dots,\ \alpha+\frac{m-1}{m}::z) \ .$$

From (5) with the conventions agreed upon in connection with (5) we may say that

$$E(\alpha,\alpha+\frac{1}{m},\dots,\alpha+\frac{m-1}{m}::z) = \sum_{r=0}^{m-1} \ \prod_{s=1}^{\nu} \Gamma(-\frac{s}{m}) \prod_{t=1}^{m-\nu-1} \Gamma(\frac{t}{m})\Gamma(\alpha+\frac{r}{m})$$

$$(11)$$

$$z^{\alpha+\frac{r}{m}} F \left(\begin{matrix} \alpha+\frac{r}{m} \ ; \ z \\ 1+\frac{r}{m},\ 1+\frac{r-1}{m},\dots,1+\frac{1}{m},1-\frac{1}{m},1-\frac{2}{m},\dots,1-\frac{m-1-\nu}{m} \end{matrix} \right)$$

wherein we have split the first product on the right side of (5) into two separate products. The F-function on the right side of (11) is sometimes also accompanied by subscripts thus: $_1F_{m-1}$.

We shall now establish the following Laplace transform theorem in which

the original function is the function of t and p is the Laplace transform

parameter whose real part is greater than 0:

$$\int_0^\infty e^{-pt} \sum_{i,-i} \frac{1}{i} E(\alpha, \alpha+\frac{1}{m}, \alpha+\frac{2}{m}, \ldots, \alpha+\frac{m-1}{m} :: \frac{ae^{i\pi}}{m^m t}) dt =$$

(12)

$$(2\pi)^{\frac{1}{2}+\frac{m}{2}} m^{-\frac{1}{2}-m\alpha} a^\alpha p^{\alpha-1} \exp\left[-a^{1/m} p^{1/m}\right]$$

where $R(\alpha) > 0$, $R(a) > 0$, $m = 2,3,4,\ldots$, and $\sum_{i,-i}$ means that in the expression

following it i is to be replaced by $-i$ and the two expressions are to be added.

To prove equation (12) we shall transform the left side into the right. We

consider therefore the left side. We substitute $t = \lambda/p$ and apply (6) in which

we let the value of $\alpha_{p+1} = 1$. This yields

$$\int_0^\infty e^{-pt} \sum_{i,-i} \frac{1}{i} E(\alpha, \alpha+\frac{1}{m}, \alpha+\frac{2}{m}, \ldots, \alpha+\frac{m-1}{m} :: \frac{ae^{i\pi}}{m^m t}) dt =$$

(13)

$$\frac{1}{p} \sum_{i,-i} \frac{1}{i} E(\alpha, \alpha+\frac{1}{m}, \alpha+\frac{2}{m}, \ldots, \alpha+\frac{m-1}{m}, 1 :: \frac{ape^{i\pi}}{m^m}).$$

We now express each E function on the right side in terms of the value given by

(11) and combine the two resulting expressions by factoring out common terms.

The terms which result from $z^{\alpha+r/m}$ in (11) are transformed by means of (8). We

also use the definition of the generalized hypergeometric function to cancel

factors in numerator and denominator. Hence the right side of the preceding

equation becomes

$$(\frac{2\pi}{p})(\frac{ap}{m^m})^\alpha \sum_{r=0}^{m-1} \left[(\frac{ap}{m^m})^{\frac{r}{m}} \Gamma(-\frac{r}{m})\Gamma(-\frac{r-1}{m}) \cdots \Gamma(-\frac{1}{m})\Gamma(\frac{1}{m})\Gamma(\frac{2}{m})\cdots\Gamma(\frac{m-1-r}{m})\right.$$

(13a)

$$\left. \cdot {}_0F_{m-1}(;1+\frac{r}{m},1+\frac{r-1}{m},\ldots,1+\frac{1}{m}, 1-\frac{1}{m}, 1-\frac{2}{m},\ldots,1-\frac{m-1-r}{m};\frac{(-1)^m ap}{m^m})\right]$$

where the notation in ${}_0F_{m-1}$ means

$${}_r\left(1+\frac{r}{m}, 1+\frac{r-1}{m}, \ldots, 1+\frac{1}{m}, 1-\frac{1}{m}, 1-\frac{2}{m}, \ldots, 1-\frac{m-1-r}{m} \middle| \frac{(-1)^r ap}{m^m}\right).$$

Now apart from the power $(ap)^\alpha$ before the summation in (13a) the expression contains powers of $(ap)^s$ where $s = 0,1,2,\ldots$ in the generalized hypergeometric function each multiplied by $\sum\limits_{r=0}^{m-1} (ap)^{r/m}$. Let us however concentrate for the moment on a particular value of s and on a particular value of r, the former in the range $0,1,2,\ldots$ and the latter in the range from 0 to $m-1$. By using the series meaning of $_0F_{m-1}$ we find that the coefficient of $(ap)^{r/m + s}$ in (13a) equals

$$\frac{2\pi}{p} \, m^{-m\alpha - r - ms}(ap)^\alpha (-1)^{ms} \; \cdot$$

(14)
$$\left[\frac{\left\{ \Gamma(-\tfrac{r}{m})\Gamma(1+\tfrac{r}{m})\cdots\Gamma(-\tfrac{1}{m})\Gamma(1+\tfrac{1}{m}) \right\}\left\{ \Gamma(\tfrac{1}{m})\Gamma(1-\tfrac{1}{m})\cdots\Gamma(\tfrac{m-r-1}{m})\Gamma(1-\tfrac{m-r-1}{m}) \right\}}{s! \left\{ \Gamma(1+\tfrac{r}{m}+s)\cdots\Gamma(1+\tfrac{1}{m}+s) \right\}\left\{ \Gamma(1-\tfrac{1}{m}+s)\cdots\Gamma(1-\tfrac{m-1-r}{m}+s) \right\}} \right].$$

We now use (8) on the numerator of this expression to obtain

$$\frac{2\pi}{p} \, m^{-m\alpha - r - ms}(ap)^\alpha (-1)^{r+ms} \frac{\pi^{m-1}}{\left\{ \sin\tfrac{\pi}{m}\sin\tfrac{2\pi}{m}\cdots\sin\tfrac{r\pi}{m} \right\}\left\{ \sin\tfrac{\pi}{m}\sin\tfrac{2\pi}{m}\cdots\sin\tfrac{m-r-1}{m}\pi \right\}} \; \cdot$$

(15)
$$\frac{1}{\Gamma(1+s)\left\{ \Gamma(1-\tfrac{m-1-r}{m}+s)\ldots\Gamma(1-\tfrac{1}{m}+s) \right\}\left\{ \Gamma(1+\tfrac{1}{m}+s)\ldots\Gamma(1+\tfrac{r}{m}+s) \right\}} \; \cdot$$

We now use the simple identity $\sin\frac{r\pi}{m} = \sin(\pi - \frac{r}{m}\pi) = \sin\frac{m-r}{m}\pi$, for $r = 1,2,\ldots$, $m-1$ in the first denominator and rewrite the factors in the second denominator with a trivial change in form. Hence (15) becomes

$$\frac{2\pi}{p} \, m^{-m\alpha - r - ms}(ap)^\alpha (-1)^{r+ms} \frac{\pi^{m-1}}{\sin\tfrac{\pi}{m}\sin\tfrac{2\pi}{m}\cdots\sin\tfrac{r\pi}{m}\sin\tfrac{r+1}{m}\pi\sin\tfrac{r+2}{m}\pi\ldots\sin\tfrac{m-1}{m}\pi} \; \cdot$$

(16)
$$\frac{1}{\Gamma(\tfrac{1}{m}+\tfrac{r}{m}+s)\Gamma(\tfrac{2}{m}+\tfrac{r}{m}+s)\ldots\Gamma(\tfrac{1}{m}+\tfrac{r}{m}+s+\tfrac{m-1}{m})} \; \cdot$$

Use of relations (10) and (7) converts (16) to

$$\frac{2\pi}{p} m^{-m\alpha-r-ms}(ap)^{\alpha}(-1)^{r+ms} \frac{n^{m-1}}{m2^{1-m}} \quad \frac{1}{m^{\frac{1}{2}-1-r-ms}(2\pi)^{\frac{m}{2}-\frac{1}{2}} \Gamma(1+r+ms)} \quad .$$

Thus the coefficient of $(ap)^{\frac{r}{m}+s}$ in (13a) becomes

$$(17) \qquad (2\pi)^{\frac{1}{2}+\frac{m}{2}} m^{-\frac{1}{2}-m\alpha} a^{\alpha}p^{\alpha-1} \frac{(-1)^{r+ms}}{\lfloor r+ms}} ,$$

which equals

$$(2\pi)^{\frac{1}{2}+\frac{m}{2}} m^{-\frac{1}{2}-m\alpha} a^{\alpha}p^{\alpha-1} \left\{ \text{coef. of}(ap)^{\frac{1}{m}(r+ms)} \text{ in the expansion of } e^{-a^{\frac{1}{m}}p^{\frac{1}{m}}} \right\} .$$

If we now consider the successive powers of $(ap)^{1/m}$ in the series expansion of $e^{-a^{1/m}p^{1/m}}$ we see that we shall get first of all the set of powers from $n = 0$ to $n = m-1$ which gives the powers of $(ap)^{r/m+s}$ for $s = 0$ and r from 0 to $m-1$. The powers from $n = m$ to $n = m+\frac{m-1}{m}$ in the exponential series gives the powers of $(ap)^{\frac{r}{m}+s}$ for $s = 1$ and r from 0 to $m-1$. More generally every power of $(ap)^{\frac{r}{m}+s}$ which is called for in (13a) (apart from the factor $(ap)^{\alpha}$ in front) is contained in the series for $e^{-a^{1/m}p^{1/m}}$ and only those powers are contained in the exponential series. Thus (13) becomes

$$\int_{0}^{\infty} e^{-pt} \sum_{1,-1} \frac{1}{1} F(\alpha,\alpha+\frac{1}{m},\alpha+\frac{2}{m},\ldots,\alpha+\frac{m-1}{m} :: \frac{ae^{i\pi}}{m^{m}t}) \, dt =$$

$$(18) \qquad (2\pi)^{\frac{1}{2}+\frac{m}{2}} m^{-\frac{1}{2}-m\alpha} a^{\alpha}p^{\alpha-1} \exp(-a^{1/m}p^{1/m}),$$

which is the desired result as stated in (12).

3. Derivation of a subsidiary equation

We wish to show that the general transform (12) or (18) reduces in the case $m = 2$ to the Laplace transform relationship between (3) and (2). For this purpose we shall first prove a subsidiary equation, namely,

(19) $\dfrac{2\pi i z^{\alpha+\beta-1}e^{-z}}{\Gamma(1-\alpha)\Gamma(1-\beta)}\ E(1-\alpha,1-\beta::z) = E(\alpha,\beta::ze^{i\pi}) - E(\alpha,\beta::ze^{-i\pi}),$

where the notation in the E-functions is explained by (11).

We re-express each of the two E-functions on the right side of (19) by means of equation (11), add similar terms, and obtain

$E(\alpha,\beta::ze^{i\pi}) - E(\alpha,\beta::ze^{-i\pi})$

(20)
$$= 2\pi i\left[\frac{\Gamma(\beta-\alpha)}{\Gamma(1-\alpha)}\ z^{\alpha}\ {}_1F_1\binom{\alpha;\ -z}{1-\alpha-\beta} + \frac{\Gamma(\alpha-\beta)}{\Gamma(1-\beta)}\ {}_1F_1\binom{\beta;\ -z}{1+\beta-\alpha}\right].$$

We now use relation (9) to write

$$= \frac{2\pi i z^{\alpha+\beta-1}}{\Gamma(1-\alpha)\Gamma(1-\beta)}\ e^{-z}\left\{\Gamma(\alpha-\beta)\Gamma(1-\alpha)z^{1-\alpha}\ {}_1F_1\binom{1-\alpha;z}{1+\beta-\alpha} + \right.$$
$$\left. \Gamma(\beta-\alpha)\Gamma(1-\beta)z^{1-\beta}\ {}_1F_1\binom{1-\beta;z}{1+\alpha-\beta}\right\}.$$

By applying (11) we obtain (19) above. Hence the subsidiary equation is established.

4. Derivation of the case m = 2

For the case m = 2 the general result (12) tells us that the transform of

(21) $\quad \dfrac{1}{I}\ E(\alpha,\alpha+\tfrac{1}{2}::\dfrac{ae^{i\pi}}{4t}) - \dfrac{1}{I}\ E(\alpha,\alpha+\tfrac{1}{2}::\dfrac{ae^{-i\pi}}{4t})$

is

(22) $\quad (2\pi)^{\frac{3}{2}}2^{-\frac{1}{2}-2\alpha}\ a^{\alpha}\ p^{\alpha-1}\ \exp(-a^{\frac{1}{2}}p^{\frac{1}{2}}).$

We shall show that the transform relationship between expressions (21) and (22) agrees with the known relationship stated in expressions (3) and (2).

We use the equality (19) to transform (21) and obtain

$$\frac{2\pi(\frac{a}{4})^{2\alpha-\frac{1}{2}}\, t^{\frac{1}{2}-2\alpha}}{\Gamma(1-\alpha)\Gamma(\frac{1}{2}-\alpha)}\quad e^{-a/4t}\ E(1-\alpha,\ \tfrac{1}{2}-\alpha\ ::\ \tfrac{a}{4t}\ ).$$

We now use equation (4) wherein we let $\nu = 2\alpha-1$ to obtain from the preceding expression

$$\frac{2\pi(\frac{a}{4})^{2\alpha-\frac{1}{2}}\, t^{\frac{1}{2}-2\alpha}}{\Gamma(1-\alpha)\Gamma(\frac{1}{2}-\alpha)}\quad e^{-a/4t}\ \frac{\pi^{1/2}\Gamma(1-2\alpha)}{2^{-2\alpha}(\frac{a}{2t})^{\alpha-1/2}}\ e^{a/8t} D_{2\alpha-1}\left(\frac{a^{1/2}}{2^{1/2}t^{1/2}}\right)\ .$$

By means of the duplication formula for the gamma function, namely,

$$\Gamma(2x) = \Gamma(x)\Gamma(x+\tfrac{1}{2})\,\frac{2^{2x-1}}{\sqrt{\pi}}$$

wherein we let $x = \frac{1}{2} - \alpha$ we may simplify the preceding expression to

$$2^{-3\alpha+\frac{3}{2}}\ \pi\ a^{\alpha}t^{-\alpha}\ e^{-a/8t}\ D_{2\alpha-1}\left(\frac{a^{1/2}}{2^{1/2}t^{1/2}}\right)\ .$$

If we now eliminate constant factors in this expression and in (24) we see that the Laplace transform relationship between (21) and (22) is identical with the Laplace transform relationship between (3) and (2).

5. The asymptotic behavior of the original function for t near 0

It is known for a wide class of original functions and their Laplace transforms that the asymptotic behavior of the original function for t near 0 determines the asymptotic behavior of the image function as $|p|$ becomes infinite (see [5], p.137). With a possible extension of this existing theorem in mind we determine here the asymptotic behavior of the original function

$$(25) \qquad (2\pi)^{-\frac{1}{2}-\frac{m}{2}}m^{\frac{1}{2}+m\alpha}\ a^{-\alpha}\sum_{i,-i}\frac{1}{i}\ E(\alpha,\alpha+\tfrac{1}{m},\ \alpha+\tfrac{2}{m},\ \ldots,\alpha+\tfrac{m-1}{m}\ ::\ \frac{ae^{i\pi}}{m^{m}t}\ ).$$

We utilize a known integral for the E-function called the Barnes integral (see [3], p. 374). For our case where the E-function contains no ρ_{s}'s and the

p parameters α_r are α, $\alpha + \frac{1}{m}$, $\alpha + \frac{2}{m}$, ..., $\alpha + \frac{m-1}{m}$, then

$$E(\alpha, \alpha + \frac{1}{m}, \alpha + \frac{2}{m}, \ldots, \alpha + \frac{m-1}{m} :: \frac{ae^{i\pi}}{m^m t}) = \frac{1}{2\pi i} \int \Gamma(s) \prod_{\nu=0}^{m-1} \Gamma(\alpha + \frac{\nu}{m} - s)(\frac{ae^{i\pi}}{m^m t})^s ds$$

where the path of integration may be taken along the imaginary axis with loops, if necessary, to have the poles $\alpha + \nu/m$ lie to the right of the contour. If we consider the summation $\sum_{i,-i} \frac{1}{i} E$ called for in (25) we note that the factor $e^{i\pi s}$ will appear in the integral representation of the first term of the sum and the factor $e^{-i\pi s}$ will appear in the integral representation of the second term. Conversion of these factors to cosine and sine terms permits combination of the two integrals and the use of (8) gives the result that (25) equals AI where I is given

$$(27) \qquad I = -\frac{1}{2\pi i} \int \prod_{\nu=0}^{m-1} \frac{\Gamma(\alpha + \frac{\nu}{m} - s)}{\Gamma(1-s)} (\frac{a}{m^m t})^s ds$$

with the same path of integration as before and where

$$A = (2\pi)^{\frac{1}{2} - \frac{m}{2}} m^{\frac{1}{2} + m\alpha} a^{-\alpha} .$$

We show next that

$$(28) \qquad \exp\left\{ (m-1)(\frac{a}{m^m t})^{\frac{1}{m-1}} \right\} \quad (2\pi)^{1 - \frac{m}{2}} (m-1)^{1/2} I = -\frac{1}{2\pi i} \int S(s)(\frac{a}{m^m t})^s ds$$

where

$$S(s) = \sum_{u=0}^{\infty} \frac{\prod\limits_{\nu=0}^{m-1} \Gamma(\alpha + \frac{u}{m-1} + \frac{\nu}{m} - s)}{\prod\limits_{r=1}^{m-1} \Gamma(\frac{u+r}{m-1}) \Gamma(1 + \frac{u}{m-1} - s)}$$

when $R(s) > R(\alpha - \frac{1}{2})$. To see this we first substitute the value of $S(s)$ in (28) and the right hand side becomes

$$(29) \qquad -\frac{1}{2\pi i} \int \sum_{u=0}^{\infty} \frac{\prod\limits_{\nu=0}^{m-1} \Gamma(\alpha + \frac{u}{m-1} + \frac{\nu}{m} - s)}{\prod\limits_{r=1}^{m-1} \Gamma(\frac{u+r}{m-1}) \Gamma(1 + \frac{u}{m-1} - s)} \left(\frac{a}{m^m t}\right)^s ds \; .$$

We interchange integration and summation. Then (29) becomes

$$(30) \qquad \sum_{u=0}^{\infty} -\frac{1}{2\pi i} \int \frac{\prod\limits_{\nu=0}^{m-1} \Gamma(\alpha + \frac{u}{m-1} + \frac{\nu}{m} - s)}{\prod\limits_{r=1}^{m-1} \Gamma(\frac{u+r}{m-1}) \Gamma(1 + \frac{u}{m-1} - s)} \left(\frac{a}{m^m t}\right)^s ds \; .$$

In (30) we change s to $s + \frac{u}{m-1}$ and obtain

$$\sum_{u=0}^{\infty} -\frac{1}{2\pi i} \left(\frac{a}{m^m t}\right)^{\frac{u}{m-1}} \frac{1}{\prod\limits_{r=1}^{m-1} \Gamma(\frac{u+r}{m-1})} \int \frac{\prod\limits_{\nu=0}^{m-1} \Gamma(\alpha + \frac{\nu}{m} - s)}{\Gamma(1-s)} \left(\frac{a}{m^m t}\right)^s ds.$$

This equals

$$\sum_{u=0}^{\infty} \left(\frac{a}{m^m t}\right)^{\frac{u}{m-1}} \frac{1}{\Gamma(\frac{u+1}{m-1}) \Gamma(\frac{u+2}{m-1}) \dots \Gamma(\frac{u+1}{m-1} + \frac{m-2}{m-1})} \; I \; .$$

We now use (7) with m-1 instead of m to obtain

$$\sum_{u=0}^{\infty} \left[\left(\frac{a}{m^m t}\right)^{\frac{1}{m-1}}\right]^u \frac{(2\pi)^{-\frac{m}{2}+1}(m-1)^{\frac{1}{2}+u}}{\Gamma(u+1)} \qquad I,$$

which equals

$$(2\pi)^{1-\frac{m}{2}} (m-1)^{1/2} \sum_{u=0}^{\infty} \left\{(m-1)\left(\frac{a}{m^m t}\right)^{\frac{1}{m-1}}\right\}^u \frac{1}{\lfloor u} \; I$$

or

$$(2\pi)^{1-\frac{m}{2}} (m-1)^{1/2} \exp\left[(m-1)\left(\frac{a}{m^m t}\right)^{\frac{1}{m-1}}\right] \; I \; .$$

With (28) established, we utilize a known asymptotic expansion of the expression on the right side of (28), which holds when $|\frac{1}{t}|$ is large

(see [4], p.296-7). By putting all the factors on the left side of (28), except I on the right, we conclude that for $|t|$ near 0, or when $\frac{1}{|t|}$ is large,

$$AI \sim A \exp\left[-(m-1)(\frac{a}{m^m t})^{\frac{1}{m-1}}\right] \left[\frac{a}{m^m t}\right]^{\frac{1}{m-1}(ma-\frac{1}{2})} \cdot$$

(31)
$$\left\{\frac{(2\pi)^{\frac{m}{2}-1}}{\sqrt{m-1}} + \frac{M_1}{(\frac{a}{m^m t})^{\frac{1}{m-1}}} + \frac{M_2}{(\frac{a}{m^m t})^{\frac{2}{m-1}}} + \ldots\right\} ,$$

wherein the coefficients M_1, M_2, ... do not depend on t. Of course the leading term in this asymptotic expansion, in view of the value of A, is

$$(2\pi)^{-\frac{1}{2}} \frac{m^{\frac{1}{2}+ma}}{\sqrt{m-1}} a^{-a} \exp\left[-(m-1)(\frac{a}{m^m t})^{\frac{1}{m-1}}\right] \left[\frac{a}{m^m t}\right]^{\frac{1}{m-1}(ma-\frac{1}{2})} \cdot$$

We now consider the special case of m = 2 and show that the result (31) agrees for this case with a known result. We suppose that $|\frac{a}{4t}|$ is large which, of course, will be the case for t near 0. We substitute m = 2 in (31) and taking account of the value of A obtain

(32)
$$e^{-a/4t}(\frac{a}{4t})^{2a-\frac{1}{2}}(2\pi)^{-\frac{1}{2}} 2^{\frac{1}{2}+2a} a^{-a} J(\frac{a}{4t}),$$

where $J(\frac{a}{4t})$ tends to 1 as $|\frac{a}{4t}|$ tends to infinity.

This result agrees with the known asymptotic expansion of the original function (3) which holds for the case m = 2 , because (see [2], p. 392, line 2)

$$D_{2a-1}\left(\sqrt{\frac{a}{2t}}\right) = \frac{2^{-2a}(\frac{a}{2t})^{a-\frac{1}{2}}}{\pi^{1/2}\Gamma(1-2a)} e^{-a/8t} E(\frac{1}{2}-a, 1-a :: \frac{a}{4t}) \cdot$$

However (see [3], p. 351, formula (13)),

$$E(\frac{1}{2}-a, 1-a :: \frac{a}{4t}) \sim \Gamma(\frac{1}{2}-a)\Gamma(1-a) J(\frac{a}{4t})$$

where $J(\frac{a}{4t}) \longrightarrow 1$ as $t \longrightarrow 0$. Hence

$$D_{2\alpha-1}\left(\sqrt{\frac{a}{2t}}\right) \sim \frac{2^{-2\alpha}(\frac{a}{2t})^{\alpha-\frac{1}{2}}}{\pi^{1/2}\Gamma(1-2\alpha)} \ e^{-a/8t} \ \Gamma(\frac{1}{2}-\alpha)\Gamma(1-\alpha)J(\frac{a}{4t}) \ .$$

Use of the Legendre duplication formula for the gamma function gives

$$D_{2\alpha-1}\left(\sqrt{\frac{a}{2t}}\right) \sim (\frac{a}{2t})^{\alpha-\frac{1}{2}} \ e^{-a/8t} \ J(\frac{a}{4t}) \ .$$

Hence the asymptotic value of the original function (3) is

$$2^{\frac{1}{2}-\alpha} \ \pi^{-1/2} \ t^{-\alpha} \ (\frac{a}{2t})^{\alpha-\frac{1}{2}} \ e^{-a/4t} \ J(\frac{a}{4t})$$

which agrees with (32).

Acknowledgment

Appendix

We now prove a relationship used in the text proper, namely,

$$(1) \qquad \int_0^\infty e^{-\mu} \mu^{\alpha_{p+1}-1} E(p;\alpha_r:q;\rho_s:z/\mu)d\mu = E(p+1;\alpha_r:q;\rho_s:z)$$

when $R(\alpha_{p+1}) > 0$. (This relationship is stated as problem 106 on p. 394 of [3].)

Proof: If $p \geq q+1$, we use the definition of the E-function ([3], p. 352, eq. (20)), namely,

$$(2)$$

$$E(p;\alpha_r:q;\rho_s:z) = \Gamma(\alpha_p) \left\{ \prod_{n=1}^q \Gamma(\rho_n-\alpha_n) \right\}^{-1} \prod_{n=1}^q \int_0^1 \lambda_n^{\alpha_n-1}(1-\lambda_n)^{\rho_n-\alpha_n-1}d\lambda_n \cdot$$

$$\prod_{n=q+1}^{p-2} \int_0^\infty e^{-\lambda_n} \lambda_n^{\alpha_n-1} d\lambda_n \int_0^\infty e^{-\lambda_{p-1}} \lambda_{p-1}^{\alpha_{p-1}-1}(1+\lambda_1\lambda_2\ldots\lambda_{p-1}/z)^{-\alpha_p}d\lambda_{p-1}$$

where $R(\alpha_n) > 0$, $n = 1,2,\ldots,p-1$, $R(\rho_n-\alpha_n) > 0$, $n = 1,2,\ldots,q$. We substitute this expression for E given by (2) with of course z replaced by z/μ into (1). We then merely place the terms involving μ and the integration with respect to μ within the innermost integral. The resulting expression is seen to be, by the very definition of the E-function,

$$(3) \qquad E(\alpha_1,\alpha_2,\ldots,\alpha_{p-1}, \alpha_{p+1}, \alpha_p:q;\rho_s:z) \ .$$

However, equation (5) of the text shows that the E-function is symmetric in the α_r and ρ_s. Hence expression (3) is equal to the right side of (1).

If $p \leq q$, we use as the value of the E-function the definition for this case ([3], p. 352, eq. (21)), namely,

$$E(p;\alpha_r:q;\rho_s:z) = \frac{\Gamma(\alpha_1)\Gamma(\alpha_2)\ldots\Gamma(\alpha_p)}{\Gamma(\rho_1)\Gamma(\rho_2)\ldots\Gamma(\rho_q)} F(p;\alpha_r:q;\rho_s: -\frac{1}{z}) \ .$$

We substitute this value of E in (1), expand the generalized hypergeometric function into the series which defines it and integrate term by term. In view of the definition of the Gamma function, the result follows at once.

References

[1] Erdélyi, A., et.al.   –   Tables of Integral Transforms, V.I, McGraw-Hill, N.Y., 1954.

[2] Erdélyi, A., et.al.   –   Tables of Integral Transforms, V.II, McGraw-Hill, N.Y., 1954.

[3] MacRobert, T.M.   –   Functions of a Complex Variable, 4th ed., Macmillan and Co., Ltd., London, 1954.

[4] Barnes, E.W.   –   The Asymptotic Expansion of Integral Functions Defined by Taylor's Series, Phil. Trans. Royal Soc., London A, 206, 1906, pp. 249-297.

[5] Van der Pol, B.L., and Bremmer, H.   –   Operational Calculus, Cambridge Univ. Press, Cambridge, 1950.

[6] Erdélyi, A., et.al.   –   Higher Transcendental Functions, V.I, McGraw-Hill, N.Y., 1953.

[7] Friedlander, F.G.   –   Diffraction of Pulses by a Circular Cylinder, Comm. Pure and Appl. Math., V.7, 1954, p. 705.

[8] Kline, M.   –   Asymptotic Solutions of Maxwell's Equations Involving Fractional Powers of the Frequency, Comm. Pure and Appl. Math., V.8, 1955, p. 595.

DISTRIBUTION LIST FOR RESEARCH REPORTS

Contract No. AF 19(604)1717

(ONE copy unless otherwise noted)

Commander
Air Force Missile Test Center
Patrick Air Force Base, Florida
ATTN: Technical Library

Commander
Air Research and Development Command
Washington 25, D.C.
ATTN: RDDL

Commander
Air Research and Development Command
Washington 25, D.C.
ATTN: Lt. Col. R.F. Bowker, RDTDRC-1

Director
Air University Library
Maxwell Air Force Base, Alabama
ATTN: CR-4582

Headquarters, USAF
Director of Research and Development
Washington 25, D.C.
ATTN: AFDRD

Commander
Wright Air Development Center
Wright-Patterson Air Force Base, Ohio
ATTN: Mr. Walter J. Portune, WCLRS-6

Commander
Wright Air Development Center
Wright-Patterson Air Force Base, Ohio
ATTN: WCLNT-5, N. Draganjac

Commander
Wright Air Development Center
Wright-Patterson Air Force Base, Ohio
ATTN: WCIRE-5, Wave Prop. Section

Air Technical Intelligence Center
Wright-Patterson Air Force Base, Ohio
ATTN: AFOIN-4Bia

Commander
Rome Air Development Center
Griffiss Air Force Base
Rome, New York
ATTN: RCSST-3

Commander
Rome Air Development Center
Griffiss Air Force Base
Rome, New York
ATTN: RCERA-1, D. Mather

Commander
Rome Air Development Center
Griffiss Air Force Base
Rome, New York
ATTN: RCFR, Dr. Burgess

Commander
Holloman Air Res. and Dev. Center
Holloman Air Force Base, New Mexico
ATTN: HDOI

Director
Evans Signal Laboratory
Belmar, New Jersey
ATTN: Mr. O.C. Woodyard

Director
Evans Signal Laboratory
Belmar, New Jersey
ATTN: Technical Document Center

Signal Corps Liaison Officer
Mass. Institute of Technology
Cambridge 39, Massachusetts
ATTN: A.D. Bedrosian

Commanding General
SC Engineering Laboratories
Fort Monmouth, New Jersey
ATTN: SCEL Technical Documents Center
        Bay 2C122

Department of the Army
Office of the Chief Signal Officer
Washington 25, D.C.
ATTN: SIGRD

Department of the Army
Office of Chief Signal Officer
Engineering and Tech. Division
Washington 25, D.C.
ATTN: SIGNET-5

Director
Ballistics Research Laboratory
Aberdeen Proving Ground, Maryland
ATTN: Ballistics Measurement Lab.

Ballistic Research Laboratories
Aberdeen Proving Ground, Maryland
ATTN: Technical Information Branch
        Victor W. Richard

Diamond Ordnance Fuze Laboratories
Washington 25, D.C.
ATTN: Guided Missile Fuze Library
        R.D. Hatcher, Chief Microwave
        Development Section

(10)Document Service Center
Armed Services Tech. Information Agency
Knott Building
Dayton 2, Ohio
ATTN: DSC-SD

Office of Technical Services
Department of Commerce
Washington 25, D.C.
ATTN: Tech. Reports Section

National Bureau of Standards
Department of Commerce
Washington 25, D.C.
ATTN: Dr. A.G. McNish

National Bureau of Standards
Department of Commerce
Washington 25, D.C.
ATTN: Gustave Shapiro

Boulder Laboratories Library
National Bureau of Standards
Boulder, Colorado
ATTN: Mrs. Victoria S. Barker, Lib.

Director
National Bureau of Standards
Central Radio Prop. Laboratory
Boulder, Colorado
ATTN: Division 14.0

Library
Division of Public Documents
U.S. Government Printing Office
Washington 25, D.C.

(2)Commander
Air Force Cambridge Research Center
Laurence G. Hanscom Field
Bedford, Mass.
ATTN: Electronics Document Room
        CROOTR-2E

(3)Commander
Air Force Cambridge Research Center
Laurence G. Hanscom Field
Bedford, Mass.
ATTN: CRRD- R.E. Hiatt

(10)Commander
L.G. Hanscom Air Field
Bedford, Mass.
CROOTR-2

Chief, Bureau of Aeronautics
Department of the Navy
Washington 25, D.C.
ATTN: Code Aer-TD-414

Chief, Bureau of Ships
Navy Department
Washington 25, D.C.
ATTN: Mr. E. Johnston, Code 838

Commander
U.S. Naval Air Missile Test Center
Point Mugu, California
ATTN: Code 366; MT-6

U.S. Naval Ordnance Laboratory
White Oak
Silver Spring 19, Maryland
ATTN: The Library

Commander
U.S. Naval Ordnance
Test Station (Code 753)
China Lake, California

Librarian
U.S. Naval Postgraduate School
Monterey, California

Director
U.S. Naval Research Laboratory
Washington 25, D.C.
ATTN: Code 1110

Director, National Security Agency
Washington 25, D.C.

Director
U.S. Naval Research Laboratory
Washington 25, D.C.
ATTN: Code 2021

Director
U.S. Naval Research Laboratory
Washington 25, D.C.
ATTN: Code 5250, J. Bohnert

Commanding Officer and Director
U.S. Navy Underwater Sound Lab.
Fort Trumbull, New London, Conn.
ATTN: Mr. C.M. Dunn

Chief of Naval Research
Navy Department
Washington 25, D.C.
ATTN: Code 427

(2)Commanding Officer and Director
U.S. Navy Electronics Lab. Lib.
San Diego 52, California

Chief, Bureau of Ordnance
Navy Department
Washington 25, D.C.
ATTN: Technical Library, Code Ad3
        Mr. H.B. Rex, Code ReS4

Chief, Bureau of Ordnance
Navy Department
Washington 25, D.C.
ATTN: Mr. C.H. Jackson, Code Re9a

Chief, Bureau of Ordnance
Navy Department
Washington 25, D.C.
ATTN: L.E. Wallingford, Code Re4f

Chief, Bureau of Aeronautics
Department of the Navy
Washington 25, D.C.
ATTN: Code Aer-EL-931

Chief Bureau of Ships
Navy Department
Washington 25, D.C.
ATTN: L.E. Shoemaker, Code 838D

(2)Commander
U.S. Naval Air Development Center
Johnsville, Pennsylvania

Commander
U.S. Naval Air Test Center
Patuxent River, Maryland
ATTN: ET-315, Antenna Section

Naval Ordnance Laboratory
Corona, California
ATTN: Library

U.S. Naval Ordnance Laboratory
Department of the Navy
Corona, California
ATTN: Dr. Robert L. Conger

U.S. Naval Ordnance Plant
Indianapolis 18, Indiana
ATTN: AD-130 (Library)

Airborne Instruments Lab., Inc.
160 Old Country Road
Mineola, New York
ATTN: Librarian

ACF Electronics
800 N. Pitt Street
Alexandria, Pennsylvania
ATTN: Tech. Library

American Machine and Foundry Company
Electronics Division
1085 Commonwealth Avenue
Boston 15, Mass.
ATTN: Technical Library
        Mrs. Rita Moravcsik, Librarian

Andrew Alford Consulting Engineers
299 Atlantic Avenue
Boston 10, Massachusetts
ATTN: Dr. A. Alford

Battelle Memorial Institute
505 King Avenue
Columbus 1, Ohio
ATTN: I-205 F -F
        Dr. Bernard H. List

Bell Aircraft Corporation
P.C. Box 1
Buffalo 5, New York
ATTN: Technical Library
        Mrs. Jasmine H. Mulcahey

Bell Telephone Labs., Inc.
Whippany, New Jersey
ATTN: Technical Information Lib.

Bendix Aviation Corporation
Pacific Division
11600 Sherman Way
North Hollywood, Calif.
ATTN: Technical Library
        J.R. Breninger, Engr. Librarian

Bendix Radio
Div. of Bendix Aviation Corporation
East Joppa Road
Towson 4, Maryland
ATTN: Res. and Development Lab. (465)
        Chief Engineer

Bjorksten Research Laboratories, Inc.
P.O. Box 265
Madison 1, Wisconsin
Attn: F.B. Korsgard, Treasurer

Boeing Airplane Company
Pilotless Aircraft Division
Seattle 14, Washington
ATTN: Pilotless Aircraft Div. Library
        R.R. Barber, Library Supervisor

Boeing Airplane Company
Wichita Division
Wichita, Kansas
ATTN: Kenneth C. Knight, Librarian

Boeing Airplane Company
Seattle Division
Seattle 24, Washington
ATTN: E.T. Allen, Librarian

Chance Vought Aircraft, Inc.
P.O. Box 5907
Dallas, Texas
ATTN: Engineering Library
        Mr. H.S. White, Librarian

Convair, A Division of General Dynamics
        Corp.
Fort Worth 1, Texas
ATTN: K.G. Brown, Div. Res. Librarian

Convair, Division of General
        Dynamics Corporation
San Diego 12, California
ATTN: Engineering Library

Cornell Aero. Laboratory, Inc.
4455 Genesee Street
Buffalo 21, New York
ATTN: Elma T. Evans, Librarian

Dalmo Victor Company
1414 El Camino Real
San Carlos, California
ATTN: Dorothea Quigley, Tech. Libr.

Dorne and Margolin, Inc.
30 Sylvester Street
Westbury, L.I., New York

Douglas Aircraft Company, Inc.
Long Beach Division
Long Beach 1, California
ATTN: Engineering Library (C-250)

Douglas Aircraft Company, Inc.
827 Lapham Street
El Segundo, California
ATTN: Engineering Library

Douglas Aircraft Company, Inc.
3000 Ocean Park Boulevard
Santa Monica, California
ATTN: Eq. Sec. Reference Files,
        Eq. Eng. A250

Douglas Aircraft Corporation
Tulsa, Oklahoma
ATTN: Technical Library

Electronic Defense Laboratory
P.O. Box 205
Mountain View, California
ATTN: Library

Electronics Research, Inc.
2300 N. New York Avenue
Evansville, Indiana
ATTN: B.H. Baldridge,
        Engineering Supervisor

Emerson and Cuming, Inc.
869 Washington Street
Canton, Mass.
ATTN: W.R. Cuming

The Emerson Electric Mfg. Company
8100 Florissant Avenue
St. Louis 21, Missouri
ATTN: Mr. E. Breslin,
        Emerson Engineering Library

Fairchild Aircraft
Division Fairchild Eng. and Airplane
Corp.
Hagerstown, Maryland
ATTN: Library

Farnsworth Electronics Company
Fort Wayne 1, Indiana
ATTN: Technical Library

Federal Telecommunication Labs.
500 Washington Avenue
Nutley 10, New Jersey
ATTN: Technical Library

Gabriel Electronics
Division Gabriel Company
Needham Heights, Mass.
ATTN: Miss Elaine Foss, Librarian

General Electric Company
Ithaca, New York
ATTN: Advanced Electronics Center
        Library, John B. Travis

General Electric Company
Electronics Park
Syracuse, New York
ATTN: Mrs. Anne Damon, Documents
        Librarian, Documents Lib.
        Bldg. 3-143

General Precision Laboratory, Inc.
63 Bedford Road
Pleasantville, New York
ATTN: Mrs. Mary G. Herbst, Librarian

Goodyear Aircraft Corp.
1210 Massillon Road
Akron 15, Ohio
ATTN: Library D/120 Plant A

Grumman Aircraft Engineering Corp.
Bethpage, L.I., New York
ATTN: Engineering Library,
        Plant No. 5

Hallicrafters Corporation
440 West 5th Avenue
Chicago, Illinois
ATTN: Library

Hoffman Laboratories, Inc.
Los Angeles, California
ATTN: Library

Hughes Aircraft Company
Microwave Laboratory
Culver City, California
ATTN: Library, Building 12
        M.D. Adcock, Head, Antenna Dept.

Hughes Aircraft Company
Culver City, California
ATTN: Research and Development Lib.

Hycon Eastern, Inc.
75 Cambridge Parkway
Cambridge, Mass.
ATTN: Mr. S. Stein, Library

International Business Machines Corp.
Military Products Division
590 Madison Avenue
New York 22, New York
ATTN: Mr. C.F. McElwain

International Business Machines Corp.
Military Products Division
Airborne Computer Laboratories
Vestal, New York
ATTN: Mr. J.J. Walsh, Dept. 528

Jansky and Bailey, Inc.
1339 Wisconsin Avenue, N.W.
Washington, D.C.
ATTN: Tech. Library, Delmer C. Ports

Henry Jasik, Consulting Engineering
61 Second Street
Mineola, New York

Jet Propulsion Laboratory
4800 Oak Grove Drive
Pasadena, California
ATTN: I.E. Newlan

Martin Katzin and Co., Consultants
711 14th Street, N.W.
Washington 5, D.C.

Lincoln Laboratory
P.O. Box 73
Lexington 73, Massachusetts
ATTN: Henry Straus, Document Rm., A-229

Lockheed Aircraft Corporation
Missile Systems Division
7701 Woodley Avenue
Van Nuys, California
ATTN: MSD Library -902, Dept. 82-10
        E.A. Blasi, Head, Antenna Lab.

Lockheed Aircraft Corporation
California Division
Engineering Library
Dept. 72-25, Plant A-1, Bldg. 63-1
ATTN: N.C. Harnois

The Glenn L. Martin Company
Denver, Colorado
ATTN: Wm. V. Foley, Engineering Lib.

The Glenn L. Martin Company
Baltimore 3, Maryland
ATTN: Engineering Library
        Antenna Design Group

Maryland Electronic Mfg. Corp.
5009 Calvert Road
College Park, Maryland
ATTN: H. Warren Cooper

Mathematical Reviews
80 Waterman Street
Providence 6, Rhode Island

The W.L. Maxon Corporation
460 West 34th Street
New York, New York
ATTN: Antenna Laboratory

McDonnell Aircraft Corporation
Box 516
St. Louis 3, Missouri
ATTN: R.D. Detrich
        Engineering Library

McMillan Laboratory, Inc.
Ipswich, Massachusetts
ATTN: Security Officer
        Document Room

Melpar, Inc.
3000 Arlington Boulevard
Falls Church, Virginia
ATTN: Engineering, Technical Lib.

Microwave Radiation Company
19223 So. Hamilton Street
Gardena, California
ATTN: Mr. Morris J. Ehrlich, Pres.

Northrop Aircraft, Inc.
Engineering Department
1000 E. Broadway
Hawthorne, California
ATTN: E.A. Freitas, Engineering
        Library, Plant III

North American Aviation, Inc.
12214 Lakewood Boulevard
Downey, California
ATTN: Technical Library,
        Dept. 991-4

North American Aviation, Inc.
Los Angeles International Airport
Los Angeles 45, California
ATTN: Engineering Technical File

Page Communications Engineers
710 14th Street, N.W.
Washington 5, D.C.
ATTN: Library

Philco Corporation Research Division
A and Lippincott Street
Philadelphia 34, Pa.
ATTN: Technical Library

Pickard and Burns, Inc.
240 Highland Avenue
Needham 94, Mass.
ATTN: Dr. J.T. de Bettencourt

Polytechnic Research and Development
Company, Inc.
202 Tillary Street
Brooklyn 1, New York
ATTN: Technical Library

Radiation Engineering Laboratory
Maynard, Mass.
ATTN: Dr. John Ruze

Radiation, Inc.
P.O. Drawer 37
Melbourne, Florida
ATTN: Technical Library
        Mr. M.L. Cox, Assistant
        Project Engineer

Radio Corp. of America
RCA Laboratories
Rocky Point, New York
ATTN: P.S. Carter, Lab. Library

RCA Laboratories
Princeton, New Jersey
ATTN: Miss Fern Cloak, Librarian
        Research Library

RCA Defense Electronic Products
Camden 2, New Jersey
ATTN: Miss J.M. Steever, Librarian
        Library 10-2

(2)The Ramo-Wooldridge Corporation
5730 Arbor Vitae Street
Los Angeles 45, California
ATTN: Margaret C. Whitnah,
        Chief Librarian, Research
        and Development Library

The Rand Corporation
Via: SBAMA Liaison Office
1700 Main Street
Santa Monica, California
ATTN: Library

Rantic Corporation
Carlabasos, California
ATTN: Technical Library

Raytheon Manufacturing Company
M and R Division
Bedford, Massachusetts
ATTN: Irving Goldstein

Raytheon Laboratory
Wayland, Massachusetts
ATTN: Document Lib., John E. Walsh
        Dept. 8974, Antenna

Raytheon Manufacturing Company
Wayland Laboratory
Wayland, Massachusetts
ATTN: Miss Alice G. Anderson, Lib.
        Wayland Library

Republic Aviation Corporation
Farmingdale, L.I., New York
ATTN: H. Stieglitz, Engineering Lib.

Rheem Manufacturing Company
Research and Development
9236 East Hall Road
Downey, California
ATTN: J.C. Joerger

Ryan Aeronautical Company
San Diego, California
ATTN: Technical Library

Sanders Associates
137 Canal Street
Nashua, New Hampshire
ATTN: N.R. Wild, Library

Sandia Corporation
P.O. Box 5800
Classified Document Division
Albuquerque, New Mexico

Sperry Gyroscope Company
Great Neck, L.I., New York
ATTN: Engineering Library
        Florence W. Turnbull,
        Engr. Librarian

Stanford Research Institute
Menlo Park, California
ATTN: Engineering Document Library
        Mrs. Beatrice Gibson, Libr.

Sylvania Electric Company
100 First Street
Waltham, Mass.
ATT: Librarian

Systems Laboratories Corporation
15016 Ventura Blvd.
Sherman Oaks, California
ATTN: Dr. W.C. Hoffman

Technical Research Group
17 Union Square West
New York 3, New York

A.S. Thomas, Inc.
161 Devonshire Street
Boston, Mass.
ATTN: A.S. Thomas

Westinghouse Electric Corp.
2519 Wilkens Avenue
Baltimore 3, Maryland
ATTN: Engineering Library
        Kent M. Mack

Wheeler Laboratories, Inc.
122 Cutter Mill Road
Great Neck, New York
ATTN: Mr. Harold A. Wheeler

Zenith Plastics Company
Box 91
Gardena, California
ATTN: Mr. S.S. Oleesky

Library
Geophysical Institute
University of Alaska
College, Alaska

Electronic Research Laboratory
Div. of Electronic Engineering
University of California
Berkeley 4, California
ATTN: S. Silver

Electronics Research Laboratory
232 Cory Hall
University of California
Berkeley 4, California
ATTN: J.R. Whinnery

California Institute of Technology
1201 E. California Street
Pasadena, California
ATTN: Dr. Charles H. Papas

Carnegie Institute of Technology
Pittsburgh 13, Pennsylvania
ATTN: Albert E. Heine

School of Electrical Engineering
Cornell University
Ithaca, New York
ATTN: Dr. Henry G. Booker

College of Engineering
University of Florida
Gainesville, Florida
ATTN: Engineering Science Library
        Professor M.H. Latour

Engineering Experiment Station
Georgia Institute of Technology
Atlanta, Georgia
ATTN: Georgia Tech. Library
        Mrs. J.H. Crosland

Technical Reports Collection
Harvard University
Gordon McKay Library
303A Pierce Hall
Oxford Street
Cambridge 38, Massachusetts
ATTN: Mrs. E.L. Hufschmidt, Librarian

Harvard College Observatory
60 Garden Street
Cambridge, Massachusetts
ATTN: Dr. Fred L. Whipple

Serials Department -220-S Library
University of Illinois
Urbana, Illinois
ATTN: Engineering Library

Antenna Section
Electrical Engr. Research Laboratory
University of Illinois
Urbana, Illinois
ATTN: EERL Library, Room 210,
        Dr. R.H. DuHamel

The Johns Hopkins University
Department of Physics
Baltimore 18, Maryland
ATTN: Professor Donald E. Kerr

Radiation Laboratory
Johns Hopkins University
1315 St. Paul Street
Baltimore 2, Maryland

Applied Physics Laboratory
The Johns Hopkins University
8621 Georgia Avenue
Silver Spring, Maryland
ATTN: Document Library

Massachusetts Institute of Technology
Research Laboratory of Electronics
Document Room 20B-221
Cambridge 39, Massachusetts

University of Michigan
Electronic Defense Group
Engineering Research Institute
Ann Arbor, Michigan
ATTN: J.A. Boyd, Supervisor

Willow Run Labs., of the Engineering
Research Institute
The University of Michigan
Willow Run Airport
Ypsilanti, Michigan
ATTN: K.M. Siegel, Head, Theory
        and Analysis Department

University of Michigan
Willow Run Laboratories
Willow Run Airport
Ypsilanti, Michigan
ATTN: Shelia Coon, Librarian

University of Minnesota
Minneapolis, Minnesota
Engineering Library
ATTN: Head Librarian
Microwave Laboratory
Electrical Engineering Dept.
Northwestern University
Evanston, Illinois
ATTN: Prof. R.E. Beam

Antenna Laboratory
Department of Electrical Engineering
Ohio State University
Columbus, Ohio
ATTN: Dr. T.E. Tice

Oklahoma University Research Found.
Norman, Oklahoma
ATTN: Technical Library
    Professor C.L. Farrar

Microwave Research Institute
55 Johnson Street
Brooklyn 1, New York
ATTN: Dr. A.A. Oliner

Polytechnic Institute of Brooklyn
55 Johnson Street
Brooklyn 1, New York
ATTN: Microwave Research Institute

Syracuse University
Dept. of Electrical Engr.
Syracuse 10, New York
ATTN: Technical Library

University of Texas
Electrical Engr. Research Lab.
P.O. Box 8026, Univ. Station
Austin 12, Texas
ATTN: John R. Gerhardt

Dept. of Physics
University of Texas
Austin 12, Texas
ATTN: Physics Library
    Claude W. Horton

Tufts University
Medford 55, Massachusetts
ATTN: Research Lab. of Physical
    Electronics
    Professor Charles R. Mingins

University of Toronto
Dept. of Electrical Engineering
Toronto, Ontario, Canada
ATTN: Prof. George Sinclair

University of Washington
Dept. of Electrical Engineering
Seattle, Washington
ATTN: Prof. G. Held

Ionosphere Research Laboratory
Pennsylvania State College
State College, Pennsylvania
ATTN: Prof. A.H. Waynick, Director

Institute of Mathematical Science
25 Waverly Place
New York 3, New York
ATTN: Mrs. JoAn Segal, Librarian

School of Electrical Engineering
Purdue University
Lafayette, Indiana
ATTN: Professor F.V. Schultz

Department of Electrical Engineering
California Institute of Technology
ATTN: Dr. Charles H. Papas

Electronics Division
Rand Corporation
1700 Main Street
Santa Monica, California
ATTN: Dr. Robert Kalaba

National Bureau of Standards
Washington, D.C.
ATTN: Dr. W.K. Saunders

Applied Mathematics and Statistics Lab.
Stanford University
Stanford, California
ATTN: Dr. Albert H. Bowker

Department of Physics and Astronomy
Michigan State University
East Lansing, Michigan
ATTN: Dr. A. Leitner

University of Tennessee
Knoxville, Tennessee
ATTN: Dr. Fred A. Ficken

California Institute of Technology
1201 E. California Street
Pasadena, California
ATTN: Dr. A. Erdelyi

Wayne University
Detroit, Michigan
ATTN: Professor A.F. Stevenson

Mathematics Department
Stanford University
Stanford, California
ATTN: Dr. Harold Levine

University of Minnesota
Minneapolis 14, Minnesota
ATTN: Prof. Paul C. Rosenbloom

Department of Mathematics
University of Pennsylvania
Philadelphia 4, Pa.
ATTN: Professor Bernard Epstein

Applied Physics Laboratory
The Johns Hopkins University
8621 Georgia Avenue
Silver Spring, Maryland
ATTN: Dr. B.S. Gouray

(2)Exchange and Gift Division
The Library of Congress
Washington 25, D.C.

Electrical Engineering Department
Massachusetts Institute of Tech.
Cambridge 39, Massachusetts
ATTN: Dr. L.J. Chu

Nuclear Development Assoc. Inc.
5 New Street
White Plains, New York
ATTN: Library

Lebanon Valley College
Annville, Pennsylvania
ATTN: Professor B.H. Bissinger

Dept. of Physics, Thaw Hall
University of Pittsburgh
Pittsburgh 13, Pa.
ATTN: Dr. Edward Gerjuoy

Dept. of Physics
Amherst College
Amherst, Massachusetts
ATTN: Dr. Arnold Arons

California Institute of Tech.
Electrical Engineering
Pasadena, California
ATTN: Dr. Zohrab A. Kaprielian

Dr. Rodman Doll
209A Emmet St.
Ypsilanti, Michigan

California Institute of Tech.
Pasadena 4, California
ATTN: Mr. Calvin Wilcox

(3)Mr. Robert Brockhurst
Woods Hole Oceanographic Inst.
Woods Hole, Massachusetts

National Bureau of Standards
Boulder, Colorado
ATTN: Dr. R. Callet

Engineering Library
Plant 5
Grumman Aircraft Corp.
Bethpage, L.I., New York
ATTN: Mrs. A.M. Gray

Mrs. Jane Scanlon
284 South Street
Southbridge, Massachusetts

Dr. Solomon L. Schwebel
3689 Louis Road
Palo Alto, California

Microwave Laboratory
55 Johnson Street
Brooklyn, New York
ATTN: Dr. Bernard Lippmann

University of Minnesota
The University Library
Minneapolis 14, Minnesota
ATTN: Exchange Division

Professor Bernard Friedman
55 Hilltop Avenue
New Rochelle, New York

Lincoln Laboratory
Massachusetts Institute of Tech.
P.O. Box 73
Lexington 73, Mass.
ATTN: Dr. Shou Chin Wang, Rm. C-351

Melpar, Inc.
3000 Arlington Boulevard
Falls Church, Virginia
ATTN: Mr. K.S. Kelleher, Section Head

Antenna Laboratory, ERD
HQ Air Force Cambridge Research Center
Laurence C. Hanscom Field
Bedford, Massachusetts
ATTN: Nelson A. Logan

Electronics Research Directorate
HQ Air Force Cambridge Research Center
Laurence G. Hanscom Field
Bedford, Massachusetts
ATTN: Dr. Philip Newman, CRRK

HQ Air Force Cambridge Research Center
Laurence C. Hanscom Field
Bedford, Massachusetts
ATTN: Mr. Francis J. Zucker

Crosley AVCO Research Labs.
257 Crescent Street
Waltham, Massachusetts
ATTN: Mr. N.C. Gerson

Antenna Research Section
Microwave Laboratory
Hughes Aircraft Company
Culver City, California
ATTN: Dr. Richard B. Barrar

Columbia University
Hudson Laboratories
P.O. Box 239
145 Palisade Street
Dobbs Ferry, New York
ATTN: Dr. M.W. Johnson

Institute of Fluid Dynamics and Applied Math.
University of Maryland
College Park, Maryland
ATTN: Dr. Elliott Montroll

Dept. of Electrical Engineering
Washington University
Saint Louis 5, Missouri
ATTN: Professor J. Van Bladel

Dept. of the Navy
Office of Naval Research Branch Office
1030 E. Green Street
Pasadena 1, California

Brandeis University
Waltham, Massachusetts
ATTN: Library

General Electric Company
Microwave Laboratory
Electronics Division
Stanford Industrial Park
Palo Alto, California
ATTN: Library

Hughes Research Laboratories
Hughes Aircraft Company
Culver City, California
ATTN: Dr. W.A. Dolid
Bldg. 12, Rm. 2529

Smyth Research Associates
3930 4th Avenue
San Diego 3, California
ATTN: Dr. John B. Smyth

Electrical Engineering
California Institute of Tech.
Pasadena, California
ATTN: Dr. Georges G. Weill

Naval Research Laboratory
Washington 25, D.C.
ATTN: Dr. Henry J. Passerini
        Code 5278 A

Dr. George Kear
10585 N. Stelling Rd.
Cupertino, California

Brooklyn Polytechnic Institute
85 Livingston Street
Brooklyn, New York
ATTN: Dr. Nathan Marcuvitz

Department of Electrical Engr.
Brooklyn Polytechnic Institute
85 Livingston Street
Brooklyn, New York
ATTN: Dr. Jerry Shmoys

Dept. of Mathematics
University of New Mexico
Albuquerque, New Mexico
ATTN: Dr. I. Kolodner

W.L. Maxon
460 W. 34th Street
New York, N.Y.
ATTN: Dr. Harry Hochstadt

Date Due